
L 600 CAM

EAN 4007841 052997









14,3 w



















30 years (Ø 4,5h

81 lm, 54 lm/W

infrared ser

ared sensor max. r

2,4 GHz Wil

Intercom system

Camera

е

Function description

Smart. Save. Intelligent. L 600 CAM is a sensor-switched camera and intercom system in one product. With integrated micro SD memory card and camera to get razor-sharp images onto the smartphone or tablet (Wi-Fi and app-based). Enclosure in aluminium and high-quality opal glass. 180° infrared motion sensor with 10 m reach. Warm-white light: 3000 K and 781 lm at 14,3 W.

Technical specifications

Dimensions (L x W x H)	131 x 78 x 305 mm
Mains power supply	220 – 240 V / 50 – 60 Hz
Mounting height max.	2,00 m
Sensor Technology	passive infrared
Output	14,3 W
Interconnection	No
Luminous flux	781 lm
Efficiency	54 lm/W
Colour temperature	3000 K
Colour Rendering Index CRI	80-89
With lamp	Yes, STEINEL LED system
Lamp	LED cannot be replaced
LED life expectancy (max. °C)	50000 h
Base	without
LED cooling system	Passive Thermo Control
With motion detector	Yes
Detection angle	180 °
Angle of aperture	45 °
Sneak-by guard	No
Capability of masking out individual segments	No
Electronic scalability	Yes

Mechanical scalability	No
Reach, radial	$r = 2 \text{ m } (6 \text{ m}^2)$
Reach, tangential	r = 10 m (157 m ²)
Photo-cell controller	Yes
Twilight setting	10 – 10000 lx
Time setting	60 s – 15 Min.
Basic light level function	Yes
Functions	lintercom system, Camera
Soft light start	Yes
Continuous light	selectable
Impact resistance	IK03
IP-rating	IP44
Protection class	1
Ambient temperature	-10 - 40 °C
Housing material	Aluminium
Cover material	Glass opal
Manufacturer's Warranty	3 years
Settings via	Wi-Fi
With remote control	Yes
PU1, EAN	4007841052997


Sensor-switched outdoor light

L 600 CAM

EAN 4007841 052997




Detection Zone




Mögliche Montagehöhe: 1,80 m – 2,00 m

Orange: radial Schwarz: tangential

Master circuit diagram



Dimension Drawing



Master/slave interconnection circuit diagram

